

WHAT IS CLAIMED IS:

1 1. A single chip set-top box integrated circuit, comprising:
2 a digital BTSC encoder that is operable to encode first and second digital audio
3 signals into a BTSC encoded signal, said first and second digital audio signals having a
4 bandwidth defined by the frequency content of said signals; and
5 a digital output modulator for receiving the BTSC encoded signal and generating
6 a modulated output signal that is provided off chip;
7 wherein the digital BTSC encoder and digital output modulator are formed
8 together on a common substrate.

1 2. The single chip set-top box integrated circuit of claim 1, wherein:
2 the digital BTSC encoder comprises (a) a sum channel processor comprising a
3 first digital filter for digitally processing a digital sum signal and (b) a difference channel
4 processor comprising a second digital filter for digitally processing a digital difference
5 signal, wherein the digital BTSC encoder operates at a sample rate that is at least
6 substantially ten times the bandwidth of the first and second digital audio signals so that
7 said digital filters in the sum channel processor and the difference channel processor
8 substantially match BTSC analog filter transform functions in both magnitude and phase;
9 and
10 the digital output modulator comprises an audio/video processor that is operable
11 to encode an audio/video signal thereby generating a Radio Frequency (RF) modulated
12 audio/video signal as the modulated output signal.

1 3. The single chip set-top box integrated circuit of claim 2, wherein the RF
2 modulated audio/video signal is a channel 3/4 RF modulated audio/video signal that is
3 provided off chip to at least one audio/visual playback device.

1 4. The single chip set-top box integrated circuit of claim 2, further
2 comprising:

3 a rate converter and FM modulator, communicatively coupled to the audio/video
4 processor, that modulates the BTSC encoded signal, thereby generating a processed audio
5 signal; and

6 a video processor, communicatively coupled to the audio/video processor, that
7 performs video processing of a composite video signal thereby generating a processed
8 video signal;

9 wherein the audio/video processor combines the processed audio signal and the
10 processed video signal into the audio/video signal.

1 5. The single chip set-top box integrated circuit of claim 1, wherein the first
2 and second digital audio signals are Pulse Code Modulation (PCM) baseband audio
3 source signals.

1 6. The single chip set-top box integrated circuit of claim 2, wherein the
2 digital output modulator comprises a Digital to Analog Converter (DAC) that is operable
3 to transform a digital signal into an analog signal.

1 7. The single chip set-top box integrated circuit of claim 6, comprising a high
2 speed clock generator for generating a first clock signal for clocking the DAC and for
3 generating a second clock signal for clocking high speed digital logic that transfers data
4 to the DAC.

1 8. The single chip set-top box integrated circuit of claim 7, wherein the first
2 and second clock signals have a phase relationship that is controlled by a phase control
3 signal.

1 9. The single chip set-top box integrated circuit of claim 1, wherein the
2 digital BTSC encoder and a digital output modulator are formed together on a common
3 silicon substrate using CMOS processing.

1 10. The single chip set-top box integrated circuit of claim 1, comprising an
2 output for providing the modulated output signal off chip to at least one audio/visual
3 playback device.

1 11. An integrated circuit that includes a digital audio/video system, the
2 integrated circuit comprising:

3 (A) a digital audio processor for BTSC encoding first and second digital audio
4 signals into an encoded audio signal, comprising sum channel processing means and
5 difference channel processing means;

6 (B) a digital video processor that processes a composite video signal, thereby
7 generating a digital video signal; and

8 (C) an audio/video processor that is operable to modulate the encoded audio
9 signal and digital video signal to generate a Radio Frequency (RF) modulated
10 audio/video signal that is provided off chip,

11 wherein the digital audio processor, digital video processor and audio/video
12 processor are formed together on a common substrate.

1 12. The integrated circuit of claim 11, wherein the digital audio processor
2 operates at a sample rate so that said sum channel processing means and the difference
3 channel processing means substantially match BTSC analog filter transform functions in
4 both amplitude and phase whereby substantially no phase compensation is required.

1 13. The integrated circuit of claim 11, wherein:
2 the digital audio processor is communicatively coupled to the audio/video
3 processor and performs audio processing on a Pulse Code Modulation (PCM) baseband
4 audio source signal to generate the encoded audio signal;
5 the digital video processor is communicatively coupled to the
6 audio/video processor to generate the digital video signal; and
7 the audio/video processor combines the encoded audio signal and the digital video
8 signal into the audio/video signal.

1 14. The integrated circuit of claim 11, wherein the audio/video processor
2 comprises a DAC that is clocked with a very high speed clock signal.

1 15. The integrated circuit of claim 14, comprising a clock generator for
2 generating the very high speed clock signal and for providing a second clock signal to

3 digital logic circuitry that transfers data to the DAC, wherein a timing relationship
4 between the very high speed clock signal and the second clock signal is programmably
5 controlled.

1 16. The integrated circuit of claim 11 integrated as part of a single chip set-top
2 box comprising an IF demodulator, a video decoder, a transport processor, a digital audio
3 processor, a high-definition MPEG video decoder, a BTSC decoder and an audio DAC.

1 17. The integrated circuit of claim 11, wherein the digital audio processor is
2 communicatively coupled to a BTSC decoder that operates cooperatively with the
3 integrated circuit to support BTSC decoding, whereby data can be exchanged between
4 the digital audio processor and the BTSC decoder to co-verify said data using an all
5 digital loopback mode.

1 18. The integrated circuit of claim 11, wherein the digital audio processor
2 operates at a sample rate that is at least approximately ten times the bandwidth of the first
3 and second digital audio signals so that no phase compensation is required in the sum
4 channel processing means or difference channel processing means to substantially match
5 BTSC analog filter transform functions in both magnitude and phase.

1 19. A method for modulating an audio/visual signal on a single integrated
2 circuit chip, comprising:

3 receiving audio data and video data on the chip;

4 digitally processing the video data on the chip to generate a composite video
5 signal;

6 digitally encoding the audio data on the chip in accordance with an audio
7 encoding standard;

8 converting the baseband encoded composite signal from a first sampling rate to a
9 second sampling rate on the chip;

10 frequency modulating an aural carrier using the converted baseband encoded
11 composite signal on the chip, thereby generating an FM modulated audio signal;

12 mixing the composite video signal and FM modulated audio signal to a
13 programmable carrier frequency on the chip, thereby generating an RF modulated
14 audio/visual signal; and
15 outputting the RF modulated audio/visual signal off chip.

1 20. The method of claim 19, wherein the RF modulated visual signal is a
2 channel 3/4 RF modulated audio/video signal.

1 21. The method of claim 19, wherein the step of digitally encoding the audio
2 data comprises using a sampling rate of at least approximately 150-200 kHz to generate a
3 baseband encoded composite signal.